

MarMonix MRCD 1

Socket & RCD Tester



Quick Spec Highlights

- **Test Voltage Range:** 0.1 V – 250 V / 40 ~ 1000 Hz
- **Operating Voltage:** 2.6 – 3.3 V
- **RCD Test Current:** >30 mA
- **Test voltage range:** 0.1V~250V/40~1kHz

Key Features

- **Fast Wiring Check:** Quickly detects correct wiring or faults.
- **RCD Test:** Validates leakage protection with >30 mA simulation.
- **NCV Detection:** visual alerts for live circuits.
- **LED Display:** Clear status of live, neutral, and earth.
- **Safety Alarms:** light alerts.
- **Portable Design:** Compact, battery-powered for field use.

Ordering Info

- **Part Number :** 7603351
- **GTIN:** 6298043998093

Package Contents

- 1 × MRCD1 (main unit)
- 2 × 1.5V AAA Battery
- 1 × User Manual
- 1 × Certificate of Conformity
- 1 × Warranty card

Specifications

Specifications	
Work Voltage	2.6 ~ 3.3 V
Test Voltage Range	0.1 V ~ 250 V / 40 ~ 1 kHz
Work Temperature	0 °C ~ 40 °C
Work Humidity	20% ~ 75% RH
Storage Temperature	-10 °C ~ 50 °C
Storage Humidity	20% ~ 80% RH
RCD Current	> 30 mA
RCD Work Voltage	220 V ± 20 V

Warranty

This device is covered by a 2-year warranty from the date of purchase, ensuring reliability and long-term support. The warranty applies to defects in materials and workmanship under normal use. It excludes consumables (fuses, disposable batteries) and damage caused by accident, misuse, modification, contamination, or operation outside specified conditions.